



## SAFE WORK PROCEDURE

### ⚠ **CRITICAL SAFETY INFORMATION** ⚠

#### BEFORE OPERATING THIS EQUIPMENT:

- You **MUST** have completed manufacturer training and been assessed as competent
- You **MUST** be listed on the authorised users list
- You **MUST** complete ALL pre-operation safety checks before every session
- You **MUST** maintain a 500mm exclusion zone during plasma operation
- You **MUST NEVER** disable safety interlocks or protective systems
- You **MUST NEVER** leave the system unattended during operation
- You **MUST NEVER** touch components during or immediately after plasma operation
- You **MUST NEVER** operate if any safety system appears faulty

### SWP Title

Operation of 3SAE Combiner Manufacturing System (CMS) for Fibre Optic Glass Processing

Prepared by: Chris Responsible supervisor/s: [To be completed]

### List the Hazards and Risk Controls as per Risk Assessment

Associated risk assessment reference: SAIL-RA-CMS-001

#### Hazards

- High-temperature plasma operation (300°C to >3000°C)
- Compressed air system at high pressure (6.2 bar / 90 psi)
- Electrical systems (dual 24V 200W power supplies)
- Optical radiation from plasma and intense lighting

- Sharp glass fibres, cleaved ends, and diamond cleaving blade
- Vacuum system operation during partial vacuum processes
- Chemical hazards from electrode materials and cleaning agents
- Ergonomic strain from precision work and prolonged operation
- Equipment complexity requiring high level of competency
- Software and control system operation

## Risk Controls

- Mandatory training and competency assessment before operation
- Complete pre-operation safety checks before every session
- Minimum 500mm exclusion zone during plasma operation
- Appropriate personal protective equipment (PPE) for all tasks
- Never operate alone as an inexperienced user (supervision required)
- Emergency stop button tested before each session
- Minimum 15-minute cooling period before accessing processing chamber
- All flammable materials removed from 1-metre radius
- Safety interlocks verified functional before operation
- Immediate reporting of any malfunctions or safety concerns
- Regular equipment inspections and maintenance
- Clear emergency procedures displayed and understood
- Authorised users list maintained and enforced

---

## List Resources Required

### Personal Protective Equipment (PPE)

- **Safety glasses (mandatory at all times):** Close-fitting design to prevent glass fragment entry; must be worn whenever handling optical fibres or operating equipment
- **Heat-resistant gloves:** Must be available and used when handling any components after plasma processing (not for use during active operation near plasma)
- **Nitrile gloves (recommended):** For handling optical fibres (provides cut protection and dexterity); mandatory when handling electrodes or cleaning chemicals
- **Laboratory coat or protective clothing:** To protect against glass fragments and potential chemical splashes
- **Closed-toe shoes (mandatory):** No open-toed footwear permitted in laboratory

### Equipment and Materials

- 3SAE Combiner Manufacturing System (CMS-01-0100)
- PC with CMS control software, monitor (23" or 40" depending on configuration)

- Optical fibres for processing (125µm to 2mm diameter as required)
- Appropriate fibre holders for diameter being processed (250µm, 400µm, 700µm, 1000µm, 1500µm, 2000µm, 2500µm)
- End cap holders if performing end cap splicing
- Electrode cleaning kit (cleaning discs provided with system)
- Spare electrode sets
- Cleaning materials for fibre preparation (isopropanol, lint-free wipes)
- Thermal inspection camera (for verifying cool-down before handling)

### **Safety Equipment (must be present in laboratory)**

- Fire extinguisher suitable for electrical fires (CO<sub>2</sub> or dry powder type) within 10 metres of equipment; location: [specify]
- First aid kit including splinter removal tools; location: [specify]
- Emergency eyewash station; location: [specify]
- Sharps disposal container for glass waste; location: within arm's reach of work area
- Emergency stop button (integrated into CMS system)
- Compressed air emergency shut-off valve; location: [specify]
- Mains power isolator for CMS; location: [specify]
- Emergency contact numbers displayed prominently
- Equipment operation logbook
- Incident report forms

### **Environmental Requirements**

- Compressed air supply: 6.2 bar (90 psi), 126 L/min (4.5 cfm) minimum
- Electrical supply: Dual 24V 200W power sources (mains supply with RCD protection)
- Adequate bench space: Minimum 1 metre clearance on all sides of equipment
- Adequate lighting: Minimum 500 lux at work surface
- Adequate ventilation: For heat dissipation and any electrode fumes
- Stable work surface: Capable of supporting 75 kg equipment weight
- Ambient temperature control: Equipment operates best in controlled environment

## **Step by Step Instructions for Undertaking the Task**

### **BEFORE STARTING - CRITICAL SAFETY REQUIREMENTS**

#### **STOP - Verify your authorisation:**

- Have you completed 3SAE CMS manufacturer training? **YES/NO**
- Have you passed the competency assessment? **YES/NO**

- Are you listed on the authorised users list? **YES/NO**
- If you answered NO to any of these: **DO NOT OPERATE - Contact supervisor**

### **Supervision requirements for new users:**

- First 10 operations: Direct supervision by experienced user required
- Next 20 operations: Experienced user must be present in laboratory
- After 30 successful operations: May operate independently if competency maintained

## **1. PRE-OPERATION SAFETY CHECKS (MANDATORY - DO NOT SKIP)**

**Complete these checks EVERY TIME before operation. If ANY check fails, DO NOT USE - lock out and report to supervisor immediately.**

### **1. Sign in to equipment logbook:**

- Record: Your name, date, time, type of operation planned
- Review previous entries for any reported issues
- Check that no maintenance or repair is scheduled

### **2. Visual inspection of equipment exterior:**

- Check for any visible damage to equipment housing or enclosures
- Verify no cables or hoses are damaged, frayed, or kinked
- Check that all cable connections are secure
- Ensure no liquid spills or contamination on or near equipment
- Verify work area is clean and free of clutter
- **If ANY damage found: DO NOT USE - lock out and report to supervisor**

### **3. Check exclusion zone and clearances:**

- Verify 500mm exclusion zone around equipment is clear
- Remove any flammable materials from 1-metre radius
- Ensure no obstructions to emergency stop button or exit routes
- Confirm adequate lighting for operation
- Check that fire extinguisher is accessible

### **4. Compressed air system checks:**

- Verify compressed air supply is connected and secure
- Check pressure gauge reads approximately 6.2 bar (90 psi)
- Listen for any unusual hissing or air leaks
- Inspect visible air lines for damage or kinks
- Test emergency air shut-off valve (close and reopen to verify function)
- **If pressure is incorrect or leaks detected: DO NOT USE - contact facilities/supervisor**

### **5. Electrical system checks:**

- Verify mains power is connected and RCD is functional (test RCD button)
- Check that no electrical cables show damage or exposed conductors
- Verify all equipment indicators show normal status
- Ensure emergency power isolation switch is accessible and functional

- **If any electrical issues detected:** DO NOT USE - contact supervisor/electrician

#### 6. Emergency stop button test:

- **CRITICAL:** Press emergency stop button to verify it functions
- System should immediately cease all operations
- Reset emergency stop and verify system can restart normally
- **If emergency stop does not function correctly:** DO NOT USE - lock out and report immediately

#### 7. Safety interlock verification:

- Verify that opening chamber door during operation triggers automatic shutdown (test with system in safe idle state)
- Check that all safety interlocks appear intact and functional
- **If any interlock appears bypassed or faulty:** DO NOT USE - report immediately

#### 8. Software and control system check:

- Power on PC and CMS control system
- Verify software loads without errors
- Check that both camera views display correctly
- Verify all system status indicators show “ready” or normal state
- **If software errors or camera failures:** DO NOT USE - contact IT/supervisor

#### 9. Vision system verification:

- Check both orthogonal camera views are clear and focused
- Verify telecentric lenses are clean (clean gently with lens tissue if needed)
- Test that monitor displays both camera feeds clearly
- Adjust monitor brightness/contrast if needed for viewing comfort
- **If vision system not functioning:** DO NOT USE - operation requires visual monitoring

#### 10. Check sharps disposal and first aid readiness:

- Verify sharps disposal container is available and not full
- Confirm first aid kit location and check it contains splinter removal tools
- Note location of emergency eyewash station
- **If safety equipment not available:** Obtain before proceeding

#### 11. Personal protective equipment (PPE) verification:

- Put on safety glasses (close-fitting type)
- Confirm laboratory coat/protective clothing is worn
- Verify closed-toe shoes are being worn
- Have nitrile gloves and heat-resistant gloves readily available
- **Never proceed without appropriate PPE**

#### 12. Final pre-operation check:

- All pre-operation checks completed satisfactorily? **YES/NO**
  - Any safety concerns or unusual observations? **Record in logbook**
  - **If any concerns:** Consult with supervisor before proceeding
  - **If all checks passed:** Proceed to operation
-

## 2. EQUIPMENT STARTUP AND INITIALISATION

### 1. Power-up sequence:

- Ensure PC and CMS software are running
- Verify compressed air supply is open and at correct pressure
- Allow system to complete initialisation sequence (typically 2-3 minutes)
- Watch for any error messages during startup
- Verify all system diagnostics show normal operation

### 2. Electrode inspection and installation (if required):

- **Put on nitrile gloves** before handling electrodes
- Open electrode chamber following software prompts or manual procedures
- Visually inspect electrodes for wear, damage, or excessive contamination
- If electrodes appear worn (consult manufacturer guidelines for wear limits): Replace with spare set
- Ensure electrodes are correctly positioned and secured
- Close electrode chamber and verify secure closure
- **Remove nitrile gloves** after electrode handling (do not contaminate other surfaces)

### 3. Cooling system verification:

- Verify embedded electrode cooling system is functioning (check for coolant flow indicators if present)
- Listen for coolant pump operation (should be quiet and steady)
- Check for any coolant leaks around electrode assembly
- **If cooling system not functioning:** DO NOT proceed - contact supervisor/manufacturer

### 4. Calibration and alignment check (if required by procedure):

- Some processes may require alignment calibration
- Follow software prompts for automatic alignment procedures
- Verify pitch and yaw alignment systems are functioning correctly
- If manual alignment needed: Use provided alignment fixtures and follow manufacturer procedures

---

## 3. FIBRE PREPARATION AND LOADING

### 1. Select appropriate fibre holders:

- Choose fibre holders matching the diameter of fibres to be processed:
  - 250µm holders for standard single-mode fibres
  - 400µm, 700µm, 1000µm, 1500µm, 2000µm, 2500µm for larger diameter fibres
- Install fibre holders in both left and right positioning stages
- Ensure holders are clean and properly seated

### 2. Prepare optical fibres:

- **Ensure safety glasses are on** before handling fibres
- Strip fibre coating if required using appropriate stripping tool (not while in CMS)
- Clean fibre ends with isopropanol and lint-free wipes
- If cleaving externally before loading: Use proper cleaving technique to achieve clean end face

- Handle fibres only by coated sections when possible
- **Use tweezers or fibre handling tools** - avoid direct hand contact with glass sections

### 3. Load fibres into holders:

- Carefully position fibre in left holder first
- Secure fibre gently (avoid over-tightening which can damage fibre)
- Load second fibre into right holder (for splicing operations)
- For tapering operations: Load single fibre as per procedure
- Verify fibres are properly seated and secured
- Check alignment visually through camera system

### 4. Position fibres using software control:

- Use X-Y-Z positioning controls to align fibres
  - Bring fibre ends into view of both camera systems
  - For fusion splicing: Align fibre cores using automatic or manual alignment
  - Achieve alignment resolution of <50nm in X and Y axes
  - Verify alignment on both orthogonal camera views before proceeding
  - **Never attempt to adjust fibre position manually while system is powered**
- 

## 4. OPERATION - FUSION SPLICING

This section covers standard fusion splicing operations. For tapering or cleaving, see sections 5 and 6.

### 1. Configure splice parameters:

- Select appropriate splice program from software library OR
- Create custom splice program specifying:
  - Arc power settings (based on fibre type and diameter)
  - Arc duration
  - Pre-splice cleaning arc (if required)
  - Overlap distance
  - Push distance during splice
- Save custom programs for repeatability
- **Test new programs on scrap fibres before using on valuable components**

### 2. Pre-splice arc cleaning (if required):

- Some fibre types benefit from pre-splice cleaning arc
- Software will prompt for this step if programmed
- Verify fibres remain aligned during cleaning arc
- Visual inspection via camera for any debris or contamination

### 3. Final pre-splice verification:

- **STOP - Safety verification before plasma activation:**
  - Hands clear of equipment? **YES**
  - Exclusion zone clear? **YES**

- Fibre alignment correct? **YES**
- Splice parameters confirmed? **YES**
- Emergency stop accessible? **YES**
- **If any NO answers:** Correct before proceeding

#### 4. Initiate fusion splice:

- Click “Start Splice” or equivalent command in software
- **PLASMA WILL NOW ACTIVATE - Stand clear**
- Monitor splice progress on both camera views
- Watch for:
  - Smooth approach of fibre ends
  - Uniform heating and melting of glass
  - Proper fusion at interface
  - Absence of bubbles or voids
- **Do NOT reach towards equipment during plasma operation**

#### 5. Post-splice monitoring:

- Software will automatically control:
  - Plasma power and timing
  - Fibre positioning and overlap
  - Push force during fusion
  - Cool-down period
- Process typically completes in 10-60 seconds depending on fibre size
- **Wait for “Splice Complete” confirmation** before proceeding

#### 6. Splice quality assessment:

- System automatically captures before/during/after images
- Visually inspect splice on monitor for:
  - Smooth, symmetrical splice junction
  - Proper alignment (minimal core offset)
  - Absence of bubbles, voids, or cracks
  - Appropriate splice geometry
- Use scanning function to measure splice diameter profile if needed
- Record splice quality in logbook (accept/reject decision)

#### 7. Cool-down period (MANDATORY):

- **DO NOT touch fibres or components for minimum 15 minutes after splice**
- Software may display temperature information
- **Use thermal inspection camera** to verify components have cooled if immediate handling required
- **Heat-resistant gloves** do not provide complete protection immediately after >3000°C plasma
- Plan work to allow proper cooling time between splices

#### 8. Remove spliced component:

- After confirmed cool-down:
  - Carefully release fibre from holders

- Use fibre handling tools (tweezers) to grip coated sections only
- Transfer to appropriate storage or testing fixture
- Dispose of any cleaved scrap fibres in sharps container immediately

#### 9. If splice is rejected:

- Cleave out the failed splice section
- Prepare new fibre ends
- Repeat alignment and splicing process
- Document failure mode in logbook for quality tracking

## 5. OPERATION - FIBRE TAPERING

Tapering operations use plasma to elongate fibre while reducing diameter. Available modes: bidirectional, single-direction, or custom table-based tapering.

### 1. Select tapering mode and parameters:

- **Bidirectional tapering:** For symmetric tapers up to 150mm length
- **Single-direction tapering:** For asymmetric tapers up to 90mm length
- **Table-based tapering:** For custom taper profiles using syntax-based programming
- Define critical parameters:
  - Taper ratio (input diameter / output diameter)
  - Taper length
  - Pulling speed profile
  - Arc power profile
  - Hot zone width (can be expanded in partial vacuum mode)

### 2. Load fibre for tapering:

- Secure fibre in both left and right holders with adequate length for taper
- Ensure sufficient fibre extends beyond holders to achieve desired taper length
- Position initial heat zone at correct starting location
- Verify load cell feedback system is functional (shows fibre tension)

### 3. Partial vacuum mode (if required):

- For adiabatic tapers or wide heat zone processing:
  - Verify vacuum chamber seals and O-rings are in good condition
  - Close chamber and verify seal integrity
  - Initiate vacuum pump following software procedure
  - Monitor pressure gauge during evacuation
  - Target pressure: [specify based on process requirements]
- **Never open chamber while under vacuum**
- Vacuum mode expands plasma heat zone up to 10x along fibre axis
- **If unusual sounds or pressure readings:** Immediately abort and vent to atmosphere

### 4. Configure taper program:

- Use simplified LabVIEW GUI for standard tapers OR
- Create custom program using table-based tapering interface OR
- Import program from MATLAB/Excel if custom algorithm developed
- Software allows 20 adjustments per second for:
  - Fibre platform positions (left and right)
  - Heat zone location
  - Arc power settings
- **Validate program with simulation or test run before using on valuable fibre**

#### 5. Initiate tapering process:

- **STOP - Final safety check:**
  - Fibre secured properly? **YES**
  - Taper parameters confirmed? **YES**
  - If using vacuum: Chamber sealed and pressure correct? **YES**
  - Exclusion zone clear? **YES**
- Click “Start Taper” command
- **PLASMA WILL ACTIVATE - Stand clear of equipment**

#### 6. Monitor tapering process:

- Watch “Hot Imaging” live view of molten glass during tapering
- Monitor load cell feedback showing fibre tension
- Verify smooth, controlled pulling motion
- Watch for taper formation via camera views
- Typical taper time: Several minutes depending on length and profile
- **Do NOT interfere with process once started**
- **If any abnormal behaviour observed:** Use emergency stop immediately

#### 7. Post-taper procedures:

- Process completes automatically when programmed taper profile achieved
- Software captures images and process data
- **Cooling period MANDATORY:** Minimum 15 minutes before handling
- If in vacuum mode:
  - Software will prompt for controlled venting
  - Allow chamber to return to atmospheric pressure
  - Verify pressure equalised before opening chamber
- **Use thermal camera** to verify taper has cooled sufficiently

#### 8. Taper quality verification:

- Use scanning function to measure taper diameter profile
- Compare measured profile to target specification
- Visual inspection for:
  - Smooth taper transition
  - Absence of modulations or stress concentrations
  - Symmetry (for bidirectional tapers)

- Proper taper length
- Record taper quality data in logbook
- **If taper meets specifications:** Proceed to removal
- **If taper is defective:** Document failure mode and repeat process

#### 9. Remove tapered fibre:

- After confirmed cool-down and quality verification
- Carefully release fibre from holders using fibre handling tools
- Support taper along entire length to prevent breakage
- Transfer to appropriate storage or next processing step
- Clean work area and dispose of scrap in sharps container

## 6. OPERATION - PRECISION CLEAVING

The CMS includes in situ ultrasonic diamond-tipped cleaving capability for production of end caps, tapers, and accurate length components.

### 1. Prepare fibre for cleaving:

- Load fibre to be cleaved in appropriate holder
- Position fibre so desired cleave location is in field of view
- Use real-time scanning to identify exact cleave position
- Achieve cleave location precision of  $\pm 12.5\mu\text{m}$  using reference marks

### 2. Configure cleaving parameters:

- Diamond-tipped blade with piezo-based frequency and amplitude control
- Set ultrasonic frequency and amplitude based on fibre diameter:
  - Larger fibres (up to  $500\mu\text{m}$ ): May require higher amplitude
  - Smaller fibres: Lower amplitude prevents shattering
- Position semi-automated backstop for blade travel limit
- **Verify blade is sharp and undamaged** (inspect through camera if possible)

### 3. Execute cleave:

- **STOP - Safety check before cleaving:**
  - Safety glasses on? **YES**
  - Hands clear of cleaving zone? **YES**
  - Fibre properly positioned? **YES**
- Initiate cleave command in software
- Ultrasonic blade will advance to fibre, vibrate, and create cleave
- Process typically completes in  $<1$  second
- **Do NOT manually interfere with cleave process**

### 4. Cleave quality assessment:

- High-resolution camera inspection of cleaved end face
- Good cleave characteristics:

- Flat, perpendicular end face
- Minimal chipping or fracture
- Clean separation
- **If cleave is poor quality:**
  - Adjust cleave parameters (frequency, amplitude, blade position)
  - May need to cleave back further and repeat
- Software captures images for documentation

#### 5. Post-cleave handling:

- Cleave fibre end is VERY SHARP
- Use extreme care when removing cleaved component
- Use tweezers or fibre handling tools only
- Place cleaved scrap immediately in sharps container
- **Never allow cleaved fibres to fall on floor or work surface**

#### 6. Cleave blade maintenance:

- Diamond blade requires periodic replacement based on usage
- Signs blade needs replacement:
  - Poor cleave quality despite parameter adjustments
  - Visible damage to blade tip
  - Inconsistent cleave results
- **Blade replacement procedure:**
  - **LOCK OUT EQUIPMENT** before accessing blade
  - Use nitrile gloves when handling blade
  - Follow manufacturer procedure for safe blade removal and installation
  - Dispose of used blade in sharps container (extremely sharp)
  - Test new blade on scrap fibre before critical cleaves

## 7. EQUIPMENT SHUTDOWN AND POST-OPERATION PROCEDURES

### 1. Prepare for shutdown:

- Complete any in-progress operations
- Remove all fibres from holders
- Collect all cleaved scrap and dispose in sharps container
- Remove any fibre holders or fixtures that are not permanent

### 2. Software shutdown sequence:

- Save any custom programs or process data
- Backup critical data if required
- Close processing software following proper exit procedure
- **Do NOT force-quit software** - may cause data loss or system errors

### 3. Plasma system shutdown:

- System will automatically cool down electrodes using embedded cooling
- Allow cooling cycle to complete (typically 5-10 minutes)
- **Do NOT power off during cooling cycle**
- System will indicate when safe to power down

#### 4. Vacuum system shutdown (if used):

- Ensure chamber is fully vented to atmosphere
- Verify pressure gauge shows atmospheric pressure
- Safe to power off vacuum pump
- Leave chamber slightly open to prevent seal damage during storage

#### 5. Compressed air shutdown:

- Close compressed air supply valve (optional - can be left on if equipment used regularly)
- If closing air supply:
  - Allow system to depressurise naturally
  - Verify pressure gauge drops to zero
  - **Do NOT disconnect pressurised lines**

#### 6. Power down sequence:

- Shut down PC in normal manner
- Switch off CMS main power
- Verify all indicator lights are off
- **Do NOT disconnect power cables while system is energised**

#### 7. Post-operation inspection:

- Visual check for any damage or issues that developed during session
- Note any unusual behaviour in equipment logbook
- Check work area for any dropped fibres or glass debris
- Verify all sharps have been disposed of properly

#### 8. Work area cleanup:

- Clean all work surfaces using damp cloth (captures glass fragments)
- **Do NOT use compressed air to clean** - will disperse glass particles
- Dispose of cleaning materials in general waste (not sharps unless glass embedded)
- Return all tools and accessories to designated storage
- Ensure fire extinguisher and emergency equipment are accessible
- Leave work area clean and ready for next user

#### 9. Sign out from equipment logbook:

- Record: End time, operations completed, component count, any issues
- Note any maintenance needs or concerns
- If any problems occurred:
  - **Complete incident report if safety-related**
  - **Tag equipment if not safe to use**
  - **Inform supervisor immediately of serious issues**

#### 10. PPE removal and hand washing:

- Remove and dispose of nitrile gloves if worn
- Remove safety glasses and store properly
- Remove laboratory coat
- **Wash hands thoroughly** after handling fibres, electrodes, or chemicals
- Inspect hands for any glass fragments (use magnification if needed)

---

## Emergency Shutdown Procedures

### EMERGENCY STOP - Use in ANY of these situations:

- Plasma operation appears abnormal (unusual colour, shape, sound, or behaviour)
- Smoke, fire, or burning smell detected
- Electrical sparking, arcing, or unusual sounds
- Compressed air leak or sudden pressure loss
- Vacuum chamber failure or unusual sounds from vacuum system
- Fibre breakage during processing causing unsafe condition
- Software crash or unresponsive controls
- Personal injury occurring
- Equipment damage visible or suspected
- Any situation where continued operation is unsafe

### EMERGENCY SHUTDOWN PROCEDURE:

#### 1. IMMEDIATELY PRESS EMERGENCY STOP BUTTON

- Large red button on equipment front panel
- Pressing will immediately shut down:
  - Plasma generation
  - All motion systems
  - Processing functions
- Emergency stop does NOT remove electrical power (use main isolator for electrical emergencies)

#### 2. If emergency stop button fails or is inaccessible:

- Turn off main power at mains isolator switch
- Close compressed air supply at emergency shut-off valve
- Evacuate area if situation is worsening

#### 3. Assess the situation:

- **Fire:** Follow fire emergency procedures (see below)
- **Electrical issue:** Do not approach equipment - call electrician
- **Compressed air failure:** Evacuate and call facilities/supervisor
- **Personal injury:** Provide first aid and call emergency services if serious
- **Equipment malfunction:** Assess damage and determine if area is safe

#### 4. **DO NOT attempt to restart equipment until:**

- Emergency condition has been completely resolved
- Equipment has been thoroughly inspected by competent person or supervisor
- Root cause of emergency has been identified and corrected
- Supervisor has authorised restart in writing
- Any necessary repairs have been completed and tested
- All safety systems verified functional

#### 5. **Complete incident documentation:**

- Fill out incident report form immediately while details are fresh
- Include: Date, time, personnel present, exact circumstances, actions taken
- Attach photos if equipment damage occurred
- Submit to supervisor and safety officer
- Complete RiskWare report if required by university policy
- Equipment may need to be locked out pending investigation

#### 6. **Lock out and tag equipment:**

- If equipment is not safe to use, attach lockout tag
- Tag must state: Date, reason for lockout, who locked out, contact details
- Only supervisor or authorised maintenance can remove lockout

### **RESETTING EMERGENCY STOP (only after emergency fully resolved and authorisation obtained):**

1. Verify that emergency condition has been completely addressed
2. Obtain supervisor approval to reset (document in logbook)
3. Rotate emergency stop button clockwise to release (or follow equipment-specific reset procedure)
4. System will require re-initialisation
5. **Perform complete pre-operation safety checks** before resuming any work
6. Test emergency stop button again to verify it functions correctly
7. Proceed with caution and monitor equipment closely for any recurring issues

---

## **Emergency Procedures for Fires, Spills or Exposure to Hazardous Substances**

### **FIRE EMERGENCY:**

1. **ACTIVATE EMERGENCY STOP** to shut down all CMS systems
2. **CLOSE COMPRESSED AIR SUPPLY** immediately at emergency shut-off valve
3. **If fire is SMALL (smaller than a wastebasket) and CONTAINED:**
  - Use appropriate fire extinguisher:

- **CO<sub>2</sub> or Dry Powder** for electrical fires
- **DO NOT use water** on electrical equipment

- Aim at base of fire, sweep side to side
- Ensure you have clear escape route behind you
- **If fire does not extinguish immediately or grows:** Evacuate

#### 4. **If fire is LARGE, SPREADING, or involves compressed gas:**

- **Evacuate area immediately**
- Close door behind you (do not lock)
- **Activate building fire alarm** (break glass at alarm point)
- **Call 000** (Emergency Services) from safe location
- Provide: Location, type of fire, any hazardous materials involved
- Evacuate to designated assembly point
- Do not re-enter for any reason

#### 5. **If clothing is on fire:**

- STOP, DROP, and ROLL to smother flames
- Use fire blanket or safety shower if available
- Once flames out, cool burned area with water
- Seek immediate medical attention

#### 6. **After fire is extinguished:**

- Do not re-enter area until declared safe by emergency services or supervisor
- Equipment must be thoroughly inspected before any restart attempt
- Complete incident report with detailed description of fire cause and damage
- Review fire safety procedures and identify any improvements needed

## **THERMAL BURN INJURY:**

### 1. **Immediately move away from heat source**

### 2. **Cool affected area under running cold water for at least 20 minutes**

- Use cool tap water, not ice
- Start cooling as quickly as possible
- Continue cooling even if pain subsides
- Remove jewellery or constricting items before swelling occurs

### 3. **Do NOT:**

- Apply ice directly to burn
- Apply butter, oil, ointments, or “home remedies”
- Break any blisters that form
- Touch burn with dirty hands or materials

### 4. **After cooling, cover burn with:**

- Sterile non-stick dressing from first aid kit
- Clean plastic wrap as alternative
- **Do NOT use fluffy materials** (cotton wool) that may stick

**5. Seek immediate medical attention for:**

- Burns larger than a 20-cent coin (5cm diameter)
- Burns to face, hands, feet, genitals, or major joints
- Burns that appear deep (white, waxy, charred, or painless)
- Burns causing severe pain or extensive blistering
- Burns from electrical source
- Burns from chemical contact
- Any uncertainty about burn severity
- **Call 000 for severe burns**

**6. For minor burns (small, superficial, not on sensitive areas):**

- Continue cooling for 20 minutes
- Apply sterile dressing
- May use over-the-counter pain relief if needed
- Monitor for signs of infection (increased pain, redness, swelling, pus)
- Seek medical review if any concerns

**7. Complete incident documentation:**

- Record details in equipment logbook
- Fill out incident report form
- Notify supervisor immediately
- Complete RiskWare report
- Investigate how burn occurred to prevent recurrence

**ELECTRIC SHOCK:**

**1. DO NOT touch the person if they are still in contact with electrical source**

- You may also be shocked

**2. Break the circuit:**

- Switch off power at mains isolator, or
- Use non-conductive material (dry wood, plastic) to move person away from source
- **Only if safe to do so**

**3. Call 000 immediately if person is:**

- Unconscious or not breathing
- Showing signs of serious shock (pale, clammy, rapid pulse)
- Burned from electrical contact

**4. If person is unconscious:**

- Check for breathing
- If trained in CPR and person not breathing: Commence CPR
- Continue CPR until emergency services arrive or person recovers

**5. If person is conscious but shocked:**

- Have them lie down and remain still
- Keep warm with blanket if available

- Treat any burns (see thermal burn procedure above)
- **Seek medical attention even if person feels “fine”** - electrical shock can cause internal injuries

#### 6. LOCK OUT AND TAG EQUIPMENT:

- Equipment that delivered shock must be locked out immediately
- Attach tag stating: “Electrical hazard - Do not use”
- Only qualified electrician can inspect and clear equipment for use

#### 7. Complete incident documentation:

- Document exact circumstances of shock
- Identify electrical fault that caused shock
- Ensure equipment is repaired before any future use
- Review electrical safety procedures

### GLASS INJURY (Cuts or Embedded Fragments):

#### 1. For minor cuts:

- Rinse wound gently with clean water
- Apply pressure with clean cloth if bleeding
- Once bleeding stopped: Apply sterile adhesive dressing
- Monitor for signs of infection

#### 2. For EMBEDDED glass fragments:

- **DO NOT attempt to remove large or deep embedded glass**
- Cover area with sterile dressing
- Seek medical attention for professional removal
- **DO NOT apply pressure over embedded glass**

#### 3. For deep cuts or severe bleeding:

- Apply direct pressure with clean cloth
- Elevate injured area above heart level if possible
- **Do NOT remove cloth if blood soaks through** - add more layers on top
- **Call 000 if bleeding is severe or does not stop within 5-10 minutes**
- Keep person calm and lying down
- Monitor for signs of shock (pale, clammy, weak pulse)

#### 4. For EYE injuries involving glass:

- **DO NOT rub eye**
- **DO NOT attempt to remove any object from eye**
- **DO NOT apply pressure to eye**
- Cover eye gently with sterile dressing (no pressure)
- **Seek IMMEDIATE medical attention at emergency department**
- **Call 000 if object embedded in eye or severe pain**
- Cover both eyes to prevent movement (injured eye will track with healthy eye)

#### 5. After treatment:

- All glass injuries, even minor, must be reported to supervisor

- Complete incident report
- Investigate how glass injury occurred
- Review handling procedures to prevent recurrence
- Ensure sharps disposal procedures are being followed

#### 6. **First aid supplies for glass injuries:**

- Sterile dressings in various sizes
- Adhesive bandages
- Splinter removal tweezers (for tiny superficial fragments only)
- Eye wash and eye pads
- Clean water for rinsing wounds

## **COMPRESSED AIR SYSTEM FAILURE / AIR BLAST:**

### 1. **ACTIVATE EMERGENCY STOP**

### 2. **CLOSE COMPRESSED AIR SUPPLY** at emergency shut-off valve

### 3. **EVACUATE AREA** if loud hissing, visible high-pressure air leaks, or flying debris

### 4. **DO NOT approach failed air lines or fittings** - high-pressure air can cause serious injury

### 5. **If injury from air blast:**

- Move to safe area away from air stream
- **Seek IMMEDIATE medical attention for suspected air embolism:**
  - Signs: Chest pain, difficulty breathing, confusion, loss of consciousness
  - **Call 000** - air embolism is life-threatening
- **Do NOT allow casualty to move excessively** - may worsen embolism
- Treat any projectile injuries (embedded objects, cuts, bruises)

### 6. **Never use compressed air to:**

- Clean clothing or body
- Direct at another person
- Blow dust or debris (creates airborne hazards)

### 7. **After system failure:**

- LOCK OUT AND TAG equipment
- Contact facilities/maintenance for pressure system inspection
- Only qualified technician can repair and re-certify compressed air system
- Complete incident report documenting failure mode

## **VACUUM SYSTEM FAILURE:**

### 1. **ACTIVATE EMERGENCY STOP**

### 2. **If catastrophic failure (implosion, explosion, or violent air inrush):**

- **Evacuate area immediately**
- **Call 000 if injuries present**

- Do not re-enter until area declared safe by supervisor or emergency services

### 3. If controlled venting or slow leak:

- Allow system to vent to atmosphere naturally
- Monitor pressure gauge
- Once at atmospheric pressure: Open chamber slowly
- Inspect for damage before any further use

### 4. Injuries from vacuum failure:

- Flying glass or debris: Treat as cuts/embedded fragments (see above)
- Noise trauma: Seek medical review if hearing affected
- Crush injuries: Seek immediate medical attention

### 5. After vacuum system failure:

- LOCK OUT AND TAG equipment
- Only qualified technician can inspect vacuum chamber and seals
- Pressure testing may be required before return to service
- Document failure mode in incident report

## CHEMICAL EXPOSURE (Electrode Materials or Cleaning Chemicals):

### 1. Skin contact:

- Immediately remove contaminated clothing
- Rinse affected area with copious running water for at least 15 minutes
- **Do NOT use neutralising agents** unless specifically directed by SDS
- If irritation persists: Seek medical attention
- Bring SDS with you to medical facility

### 2. Eye contact:

- **Immediately flush eye with water or eyewash for at least 15 minutes**
- Hold eyelids open to ensure thorough rinsing
- Remove contact lenses if present and easy to remove
- **Seek immediate medical attention** after flushing
- Bring SDS to medical facility

### 3. Inhalation:

- Move to fresh air immediately
- Loosen tight clothing
- If breathing difficulty: Seek immediate medical attention
- **Call 000 if severe respiratory distress**
- Bring SDS to medical facility

### 4. Ingestion (unlikely but possible):

- **Do NOT induce vomiting** unless directed by Poisons Information
- Rinse mouth with water
- **Call Poisons Information Centre: 13 11 26**
- Follow their advice

- Seek medical attention
- Bring chemical container or SDS

**5. After chemical exposure:**

- Complete incident report
- Review SDS and handling procedures
- Identify how exposure occurred and implement prevention

**SOFTWARE / CONTROL SYSTEM FAILURE:**

**1. Attempt emergency stop via software interface** (if responsive)

**2. If software unresponsive:**

- **Press physical emergency stop button**
- **If both fail:** Turn off power at mains isolator

**3. Record any error messages or system state:**

- Take photo of screen if possible and safe
- Note exact sequence of events leading to failure
- **Do NOT attempt to troubleshoot during active emergency**

**4. After system is stopped:**

- **DO NOT attempt to restart**
- LOCK OUT AND TAG equipment
- Contact IT support or manufacturer technical support
- Only qualified technician can diagnose and repair software/control issues

**5. Data preservation:**

- If safe to do so, attempt to save any critical process data before complete shutdown
- System logs may help diagnose software failure

**6. Complete incident report** documenting software failure and any equipment impact

**EMERGENCY CONTACTS:**

- **Emergency Services:** 000
  - Police, Fire, Ambulance
  - Call for: Fires, serious injuries, life-threatening situations
- **Poisons Information Centre:** 13 11 26
  - 24/7 advice for chemical exposures and ingestions
- **University Security (after hours):** [Insert number]
  - For emergencies outside business hours
  - Can contact emergency services and key personnel
- **Supervisor:** [Name and number]
  - First point of contact for equipment issues
  - Can authorise equipment restart after emergencies
- **Safety Officer:** [Name and number]
  - For incident reporting and safety advice

- For hazard assessments and risk management
  - **First Aid Officers:** [Names and contact details / Notice board location]
    - Trained in emergency first aid
    - Can provide immediate assistance for injuries
  - **Facilities Management:** [Insert number]
    - For electrical, plumbing, HVAC emergencies
    - For compressed air system issues
  - **IT Support:** [Insert number]
    - For software and computer system issues
    - Can assist with data recovery
  - **3SAE Technical Support:** +1 615-778-8812
    - Manufacturer support for equipment issues
    - Email: info@3sae.com
    - Available during US business hours (may have time zone delay)
- 

## Clean Up and Waste Disposal Requirements

### AFTER EACH USE - CLEANING PROCEDURES:

#### Processing Chamber and Fibre Holders:

- Remove all fibre remnants from holders using tweezers
- Inspect holders for glass debris or contamination
- Wipe holders with lint-free cloth if needed
- **Do NOT use solvents on fibre holders** unless specified by manufacturer
- Return holders to designated storage

#### Electrode Cleaning (Periodic - follow manufacturer schedule):

- **Performed when:** Electrodes show visible contamination, or per manufacturer interval (typically after X hours of use)
- **Safety requirements:**
  - Equipment must be powered off and cool
  - Wear nitrile gloves
  - Perform in well-ventilated area
- **Procedure:**
  - Remove electrode assembly following manufacturer instructions
  - Use provided electrode cleaning discs
  - Clean electrode surfaces gently to remove oxidation or deposits
  - Inspect for wear (replace if worn beyond manufacturer limits)
  - Reinstall electrodes ensuring proper positioning

- **Disposal:** Used cleaning discs in general waste; worn electrodes in sharps container or per manufacturer instructions

### **Camera Lenses and Optics:**

- Inspect telecentric lenses for dust or contamination
- Clean ONLY with proper lens tissue and lens cleaner
- **Never use:** Paper towel, cloth, or harsh chemicals (will scratch lenses)
- Clean gently in circular motion from centre outward
- If optics are heavily contaminated: Contact supervisor (may need professional cleaning)

### **Work Area and Benchtop:**

- Remove all materials, tools, and personal items
- Wipe down work surface with damp cloth to capture glass fragments
- **Do NOT use compressed air to clean benchtop** - disperses glass particles into air and onto equipment
- Check for dropped fibres on floor or adjacent surfaces
- Leave work area clean and organised for next user

### **WASTE DISPOSAL:**

#### **Glass Waste (Fibre Scraps, Cleaved Ends, Broken Components):**

- **All glass waste goes in sharps container** - NEVER in general waste
- This includes:
  - Cleaved fibre ends
  - Failed splices or tapers
  - Broken fibres
  - Any glass fragments
- Sharps container should be:
  - Puncture-proof rigid container
  - Clearly labelled "Glass Sharps"
  - Positioned within easy reach of work area
  - Never filled beyond 3/4 full
- When full: Contact waste management for sharps container replacement

#### **Electrode Waste:**

- Worn electrodes: Sharps container or follow manufacturer disposal instructions
- May contain metal materials requiring specific disposal
- Contact waste management if uncertain

#### **Chemical Waste (Cleaning Agents, Isopropanol, etc.):**

- Small quantities of isopropanol used for fibre cleaning: Can evaporate or dispose via solvent waste
- Larger quantities or other chemicals: Use university chemical waste system
- Never pour chemicals down sink unless specifically approved

- Label all waste containers clearly
- Consult SDS for disposal requirements

### **General Waste:**

- Non-contaminated packaging materials
- Paper towels (that haven't contacted glass)
- Disposable gloves (if not contaminated with chemicals)
- General laboratory waste

### **Recycling:**

- Fibre spools and packaging may be recyclable
- Check with waste management for specific requirements
- Remove all labels and contamination before recycling

## **PERIODIC MAINTENANCE CLEANING:**

### **Weekly:**

- Thorough wipe-down of equipment exterior
- Vacuum or damp-wipe floor area around equipment
- Check that all waste containers have adequate capacity
- Inspect work area organisation and storage

### **Monthly:**

- Detailed cleaning of all accessible surfaces
- Inspection of air filters (if present) and cleaning if needed
- Check cable routing and organisation
- Review housekeeping procedures with all users

### **Annually (or per manufacturer schedule):**

- Professional equipment cleaning and maintenance
- Inspection and cleaning of internal components by qualified technician
- Replacement of any worn or deteriorated parts
- Calibration and alignment verification

## **MAINTENANCE LOG:**

- Document all cleaning and maintenance activities in equipment logbook
  - Record: Date, type of cleaning/maintenance, person performing, any issues noted
  - Track electrode replacement and usage hours
  - Schedule and track periodic maintenance tasks
-

## References Used in the Development of This SWP

- AS/NZS 60825.1:2014 - Safety of laser products
- AS/NZS 3000:2018 - Electrical installations (Wiring Rules)
- AS 2243 Series - Safety in laboratories
- AS 4343:2014 - Pressure equipment - Hazard levels
- Work Health and Safety Act 2011
- Work Health and Safety Regulation 2017
- 3SAE CMS Product Information Sheet (<https://3sae.com/wp-content/uploads/2024/01/CMS.pdf>)
- 3SAE CMS Operator's Manual and User Documentation
- 3SAE Combiner Manufacturing System technical specifications
- Manufacturer training materials (3SAE Technologies Inc.)
- Risk Assessment SAIL-RA-CMS-001
- University WHS policies and procedures
- Material Safety Data Sheets for all chemicals used with equipment
- Code of Practice: Managing electrical risks in the workplace

## Competency Required

### MANDATORY TRAINING (Must be completed before authorisation):

All training must be documented and records maintained by supervisor.

#### 1. Manufacturer Training Course

- **3SAE CMS Multi-day On-site Installation and Operational Training (TRN-01-0012)**
- Key learning outcomes:
  - Equipment overview and capabilities
  - Safety systems and emergency procedures
  - Control software operation (LabVIEW GUI)
  - Fusion splicing techniques and parameters
  - Fibre tapering methods (bidirectional, single-direction, table-based)
  - Precision cleaving operation
  - Electrode maintenance and replacement
  - Troubleshooting and diagnostics
  - Best practices for different fibre types and diameters
- **This training is ESSENTIAL - no substitutes**
- Training typically 2-3 days depending on applications
- Certificate of completion must be obtained

## 2. Laboratory Safety Induction

- General laboratory safety requirements
- Emergency procedures and assembly points
- Location and use of safety equipment (fire extinguishers, eyewash, first aid)
- Chemical safety and SDS interpretation
- Incident reporting procedures
- Personal protective equipment requirements

## 3. Fibre Optic Handling and Safety

- Optical fibre types and characteristics
- Safe handling techniques for glass fibres
- Hazards of glass fragments and cleaved ends
- Proper use of fibre handling tools
- Sharps disposal procedures
- First aid for glass injuries
- Eye protection requirements

## 4. Electrical Safety Awareness

- Basic electrical hazards
- Lockout/tagout procedures
- RCD function and testing
- Emergency power isolation
- When to contact qualified electrician
- **Do NOT attempt electrical repairs without qualifications**

## 5. High-Temperature Process Safety

- Thermal hazards from plasma operation
- Safe distances and exclusion zones
- Cooling time requirements
- Recognition of hot surfaces
- Thermal burn first aid
- Heat-resistant glove use and limitations

## 6. Compressed Air and Vacuum Systems Safety

- Hazards of high-pressure systems
- Safe connection and disconnection procedures
- Pressure monitoring and relief
- Vacuum chamber operation
- Emergency shutdown procedures
- Compressed air safety (never direct at body)

## **COMPETENCY ASSESSMENT:**

**Competency must be formally assessed and documented before independent operation.**

### **Theory Assessment:**

Written test or oral examination covering:

#### **1. Safety-Critical Knowledge (Must achieve 100% on these questions):**

- Emergency stop procedure and location
- Emergency shutdown for different emergency types
- Thermal burn first aid procedures
- Glass injury prevention and first aid
- Electrical safety and when to evacuate
- Compressed air system hazards
- When operation must stop (red flags)
- PPE requirements for different tasks

#### **2. Equipment Knowledge (Minimum 80% pass mark):**

- CMS capabilities and specifications
- Fusion splicing principles and parameters
- Tapering methods and applications
- Cleaving operation and quality assessment
- Software interface and control functions
- Electrode function and maintenance
- Cooling system purpose
- Vision system operation

#### **3. Procedure Knowledge (Minimum 80% pass mark):**

- Pre-operation safety checks
- Fibre preparation and loading
- Splice parameter selection
- Taper program configuration
- Cleave positioning and execution
- Shutdown procedures
- Cleaning and waste disposal
- Documentation requirements

**Failed assessment:** Review training materials, additional instruction, retest

### **Practical Assessment:**

Supervised practical demonstration of competency in:

#### **1. Pre-Operation Procedures:**

- Complete all safety checks correctly
- Identify and test emergency stop

- Verify safety equipment presence
- Set up work area appropriately
- Don proper PPE

## 2. **Basic Operation:**

- Power up system correctly
- Inspect and install electrodes
- Load fibres into holders safely
- Achieve proper fibre alignment
- Execute a simple fusion splice
- Assess splice quality
- Properly shutdown system

## 3. **Advanced Operation (as applicable to user's role):**

- Configure and execute taper program
- Perform precision cleave
- Use scanning functions
- Operate vacuum system (if required)
- Create custom splice/taper parameters

## 4. **Emergency Response:**

- Demonstrate emergency stop activation
- Describe appropriate response to different emergency scenarios
- Locate and identify use of emergency equipment
- Demonstrate understanding of when to evacuate vs. respond

## 5. **Housekeeping:**

- Proper cleanup procedures
- Correct waste disposal
- Appropriate documentation in logbook

## **Assessment Requirements:**

- Assessor must observe ALL practical elements
- Any safety-critical errors result in immediate FAIL - retraining and reassessment required
- Minor non-safety errors: Corrective instruction provided, reassessment of that element only
- All elements must be demonstrated competently before authorisation granted

## **ONGOING REQUIREMENTS:**

### **Refresher Training:**

- **Annual refresher** required for all authorised users
- Covers:
  - Safety procedure updates
  - Any equipment modifications or new capabilities
  - Review of common errors or incidents

- New techniques or best practices
- Changes to Australian Standards or regulations

### **Retraining Required When:**

- Any safety incident involving this equipment (immediate retraining)
- Safety procedures are updated or changed
- Equipment is significantly modified or upgraded
- Unsafe practices are observed (remedial training)
- Extended period of non-use (>6 months requires supervised refresher)
- New applications or techniques are implemented
- User requests refresher training

### **Supervision Requirements:**

Based on experience level:

- **Novice users (0-10 operations):**
  - Direct supervision required at all times
  - Supervisor must be experienced CMS user
  - Supervisor present in same room, actively observing
  - Each operation reviewed with supervisor before and after
- **Intermediate users (11-30 operations):**
  - Experienced user must be present in laboratory
  - Supervisor available for consultation
  - Can perform routine operations independently with oversight
  - New or complex operations require direct supervision
- **Experienced users (31+ operations, demonstrated consistent competency):**
  - May operate independently
  - Should consult with colleagues for unusual situations
  - Responsible for mentoring and supervising novice users
  - Maintain competency through regular use (minimum monthly)

### **Medical Monitoring:**

- Not routinely required for CMS operation
- Eye examinations recommended for frequent users (discuss with OH&S)
- Any health concerns affecting ability to operate safely must be reported to supervisor
- Vision requirements: Must be able to view monitor clearly and distinguish alignment on camera views

### **RECORD KEEPING:**

Documentation required for competency management:

#### **1. Training Records:**

- Manufacturer training certificate (keep copy)

- Laboratory safety induction completion
- All supplementary training courses
- Refresher training attendance
- Maintained by supervisor, copies in personnel files

## 2. **Competency Assessments:**

- Theory assessment results (written test or oral exam notes)
- Practical assessment checklist (signed by assessor)
- Date competency achieved
- Any remedial training and reassessment
- Maintained by supervisor

## 3. **Authorised Users List:**

- Current list of all authorised users
- Date authorised, authorisation level
- Displayed prominently near equipment
- Updated when users added or removed
- Reviewed annually, remove inactive users

## 4. **Individual Operation Logs:**

- Each user's operation count tracked in logbook
- Helps determine supervision requirements
- Identifies when refresher training may be beneficial
- Reviewed during annual competency review

## 5. **Incident and Near-Miss Records:**

- Any safety incidents involving specific users
- May trigger retraining requirements
- Pattern analysis for systemic issues
- Maintained by safety officer

## **COMPETENCY RENEWAL:**

- Annual competency review by supervisor
  - Considers:
    - Frequency of equipment use
    - Any incidents or near-misses
    - Refresher training completion
    - Observed work practices
    - Changes in procedures or equipment
  - Supervisor may require reassessment if concerns identified
  - Users who have not operated equipment in >12 months: Full reassessment required
-

# Staff Approved to Assess Competence for This SWP

## Authorised Assessors:

The following staff members are authorised to assess competency for this procedure:

- [Name 1] ([Role - e.g., Senior Research Fellow]) - Contact: [email/phone]
- [Name 2] ([Role - e.g., Laboratory Manager]) - Contact: [email/phone]
- [Additional names as appropriate]

## Assessor Requirements:

To be authorised as an assessor, staff must:

- Have completed 3SAE manufacturer training course
- Have minimum 100 successful operations on CMS (extensive experience)
- Demonstrate expert-level knowledge of all CMS functions and safety systems
- Have no significant safety incidents on record
- Understand adult learning principles and assessment techniques
- Be approved by laboratory manager AND safety officer
- Maintain current competency through regular equipment use

## Assessment Process:

### 1. Trainee completes all mandatory training modules

- Manufacturer training (TRN-01-0012)
- Laboratory safety induction
- Supplementary safety training (electrical, high-temp, compressed air, etc.)
- Trainee reviews this SWP and associated Risk Assessment thoroughly

### 2. Assessor conducts theory assessment

- Written test or structured oral examination
- Safety-critical questions must achieve 100%
- General knowledge questions minimum 80%
- If failed: Review materials, additional instruction, retest

### 3. Assessor supervises practical demonstration

- Trainee demonstrates all required practical skills
- Assessor uses practical assessment checklist
- Any safety-critical errors result in immediate fail
- Corrective instruction provided for minor errors

### 4. Assessor verifies competency in all required areas

- Reviews theory and practical assessment results
- Confirms all elements demonstrated satisfactorily
- Ensures trainee understands limitations and when to seek help

- Verifies trainee can respond appropriately to emergencies

**5. If competent: Assessor signs trainee off on sign-off sheet**

- Assessor signature authorises trainee for operation
- Date of authorisation recorded
- Supervision requirements specified (based on experience level)
- Trainee added to authorised users list

**6. If not yet competent:**

- Specific deficiencies identified and communicated
- Additional training and supervised practice required
- Reassessment scheduled once trainee ready
- May be partial reassessment (only areas that were deficient)

**7. Once signed off: Trainee added to authorised users list**

- Name added to list displayed near equipment
- Date authorised and authorisation level recorded
- Supervision requirements clearly noted
- Laboratory manager notified

**Authorised Users List Maintenance:**

- **Maintained by:** Laboratory Manager
- **Displayed:** Prominently near CMS equipment (visible to all users)
- **Updated when:**
  - New users authorised (add name, date, supervision level)
  - Users move to different supervision levels (update status)
  - Users become inactive (remove or mark inactive)
  - Users require retraining (temporarily suspend if safety issue)
- **Reviewed:** Annually as part of SWP review
- **Format:**

Name	Date Authorised	Authorisation Level	Supervision Required	Authorised By	Notes
[Name]	[DD/MM/YYYY]	[Novice/Intermediate/Experienced]	[Direct/Oversight/Independent]	[Assessor Name]	[Any special conditions]

**SWP Sign Off Sheet**

**SWP name and version:** Operation of 3SAE Combiner Manufacturing System (CMS)

**Version:** 1.0 - January 2026

**Reference:** SAIL-SWP-CMS-001

In signing this section the assessor agrees that the following persons are competent in following this SWP.

Name	Signature	Date Competent	Authorisation Level	Name of Assessor	Assessor Signature

**Authorisation Levels:**

- **Novice:** Requires direct supervision (0-10 operations completed)
- **Intermediate:** Requires experienced user in laboratory (11-30 operations completed)
- **Experienced:** Approved for independent operation (31+ operations, demonstrated consistent competency)

**Document Review Schedule**

This SWP must be reviewed:

- **Annually** (by January 2027, then annually thereafter)
- After any incident involving this equipment or process
- When equipment is modified, upgraded, or repaired
- When new hazards are identified or new information becomes available
- When procedures change or new applications are implemented
- When Australian Standards are updated or new regulations introduced
- When manufacturer issues safety bulletins or updates
- If patterns of user errors or near-misses are identified

**Review Process:**

1. Collect feedback from all users

2. Review incident reports and near-miss records
3. Check for equipment modifications or updates
4. Verify all safety controls remain effective
5. Update procedures as needed
6. Re-train all users on significant changes
7. Document review completion in equipment logbook

**Version Control:**

- Version number incremented for all changes
- Change history documented
- All users notified of updates
- Superseded versions archived (not destroyed - maintain history)

*End of Safe Work Procedure*

**Document Control:**

- This is a DRAFT document requiring review and approval
- All bracketed items [To be completed] must be filled in before approval
- This document must be approved by the Safety Officer and supervisors before use
- This SWP is based on Risk Assessment SAIL-RA-CMS-001
- Once approved, all authorised users must be trained on this SWP
- Users must sign the competency sign-off sheet before independent operation
- This document must be readily available to all users (printed copy near equipment, electronic copy accessible)

**Related Documents**

- Risk Assessment - 3SAE CMS - Hazard identification and risk controls
- Manufacturer Product Information - Official 3SAE CMS specifications

**Document Control**

Version	Date	Author	Changes
1.0	January 2026	Chris Betters	Initial release